



➤ Elma 6100BT IP65 True RMS Multimeter with Bluetooth

Free APP and build in, bright LED torch light

Elma 6100BT is a rugged true RMS AC/DC mini multimeter equipped with Bluetooth function. The instrument measures current, voltage, frequency, capacitance, resistance and continuity. Furthermore, the instrument provides a custom range for external current clamp, measuring as much as 3000A using the flexible clamp ElmaFlex 430.

Using the Bluetooth function and free app, Elma Link, available for both iOS and Android, Elma 6100BT becomes a safe and clever documentation tool. Watch the display directly on your Android/iOS device and perform measurements in safe distance from dangerous voltage. Watch and record all values and trends directly on your phone. Save and attach comments to measurements and share e.g. by mail.

Elma 6100BT is equipped with back lit display and bright LED torch light, data hold, max/min and auto power off. The instrument fulfills EN61010-1 CAT III 600V and is delivered with test leads, batteries and manual.



Attribute	Value
Voltage AC/DC	0...600m...6...60...600V
Accuracy	AC: $\pm 1,0\%$ + 5D, DC: $\pm 1,0\%$ + 3D
Current AC/DC	0-600 μ -6000 μ -60m-600m-10A
Resistance	0...600...6k...60k...600k...6M...60M Ω
Frequency	10Hz...10MHz
Capacitance	0...60n...600n...6 μ ...60 μ ...600 μ ...6000 μ F
Display	3 6/7 digit, 6000 counts
Batteries	2 stk. 1,5V LR03 AAA (Incl.)
Dimensions	121x67x35mm
Weight	190g