



➤ Elma X One True RMS multi and voltage tester - with open current clamps

The Elma X ONE is a smart true RMS multi tester which combines professional voltage tester with open current clamps.

This slim design RMS multi tester is suitable for work with the power on.

The Elma X One comes with batteries, test leads, manual and bag that fits to a belt.

Features:

- Voltage test, 2 pole with LEDs 12...1.000V AC/DC
- True RMS voltage measurement with display 7...1.000V AC/DC
- True RMS current measurement with very slim current clamps 0-200A
- Resistance measurement 0-50kΩ and continuity test
- Voltage test, 1 pole, indicating phase
- Phase rotation test, 2 pole
- Large clear illuminated display and bright LEDs
- Self-test and auto on/off function
- True voltage test also without batteries - suitable for work with the power on
- Meets the voltage tester directive for working with the power off
- Very powerful interchangeable test leads with 4mm standard plug
- Interchangeable test leads tips 2/4mm
- Built-in powerful flashlight

Attribute	Value
Voltage indication:	12, 24, 50, 120, 230, 400, 690 & 1000V AC/DC
Digital display LCD	7.0-1000V AC/DC
Test Current:	< 3.5mA
Current:	0-200.0A AC
Voltage detector (1 pole):	90-1000V AC
Resistance:	0-50kΩ
Phase rotation:	2 pole, 90-1000V 45-65Hz
Working temperature:	-15...55°C
Safety:	IEC 61010-1 CAT IV 600V / CAT III 1000V. IEC 61243-3:2014
Protection class:	IP65
Display:	9999
Clamp opening:	16mm
Battery:	2x1,5V LR03 (inkl.)
Dimensions:	220x57x35 mm
Weight:	220g

